



通讯协议

Communications agreements

版本V1.0

V1.0 version



版本修订记录 Revision records

| 序号 Serial number | 描述 Description | 日期 Date | 版本 Version | 作者 Author |
|------------------|----------------------|------------|------------|-----------|
| 1. | 初始版本 Initial version | 2019.06.11 | V1.0 | |
| | | | | |

1.物理层 physical layer

1.1 UART

| | | |
|-------------------------------|----------------------------|---|
| 1. 物理接口 physical interface | UART | |
| 2. 波特率 baud rate | 9600 bps | |
| 3. 通讯格式 Communications Format | 9600 , N , 8 , 1 | |
| 4. 有效电平 effective level | 发送 TXD TXD sent | “0”: <0.5V “1”: OC (耐压100V Voltage should lower than 100V) |
| | 接收 RXD RXD received | “0”: <0.5V “1”: >3V(耐压100V Voltage should lower than 100V) |

2.通讯格式 Communications Format

2.1 基本时序 Basic timing

所有消息均由主机发送，所有从机收到消息后判断从机地址是否吻合，只有在从机地址吻合情况下才允许向主机返回数据。

All messages are sent by the host, all slave after receiving the message to determine whether the slave address match, only in the case of slave address match is allowed to return data to the host.

.2 地址分配 Address allocation



| 模块Module | 地址Address |
|-----------------------|-----------|
| BMS主控BMS Master | 0x01 |
| 蓝牙手机APP Bluetooth APP | 0x20 |
| GPRS | 0x40 |
| 上位机Upper | 0x80 |

2.3 UART通讯格式UART Communication formats

2.3.1 上位机发送upper computer

| 帧头Frame Head Start Flag | 上位机地址 Upper secondary address 通信模块地址 Communication module address | 数据ID Data ID | 数据长度 Data Length | 数据内容 Data | 校验和 Checksum (1 byte) |
|----------------------------|--|------------------------|-----------------------------|--------------|-----------------------------|
| 0xA5 (固定) Fixed | 0x80(UPPER-Add) | 参考第6节 See Section 6 | 8字节 (固定) 8 bytes (fixed) | | |

2.3.2 从机响应主机命令slave response host command

| 帧头 Start Flag | 通信模块地址 Communication module address | 数据ID Data ID | 数据长度 Data Length | 数据内容 Data | 校验和 Checksum (1 byte) |
|------------------|--|------------------------|-----------------------------|--------------|-----------------------------|
| 0xA5(固定)Fixed | 0x01(BMS-Add) | 参考第6节 See Section 6 | 8字节 (固定) 8 bytes (fixed) | | |

Note:

对于每一个数据,都有固定的数据长度,一次不能读取两个数据。For each data, there is a fixed data length, two data can not be read at a time.
检验为之前所有数据之和(只取低字节)。Check as the sum of all previous data (take only low bytes).



3 通讯内容信息 Communications content information

| 数据 Message | 数据ID Message ID | UPPER - BMS | 说明 Remark |
|--|-----------------|-------------|--|
| 总压电流SOC SOC of Total Voltage Current | 0x90 | 发送Send | Byte0~Byte7:Reserved |
| | | 返回Return | Byte0~byte1 : 累计总压 (0.1V) pressure (0.1 V) Byte2~byte3 : 采集总压 (0.1V) acquisition (0.1 V) Byte4~byte5 : 电流 (30000 Offset, 0.1A) current (Offset,0.1A 30000) Byte6-Byte7 : SOC (0.1%) |
| 单体最高最低电压Ma ximum Minimum Voltage of Monomer | 0x91 | 发送Send | Byte0~Byte7:Reserved |
| | | 返回Return | Byte0~byte1 : 最高单体电压值 (mV) maximum monomer voltage (mV) Byte2 : 最高单体电压cell号 Maximum Unit Voltage cell No. Byte3~byte4 : 最低单体电压值 (mV) minimum monomer voltage (mV) Byte5 : 最低单体电压cell号 Minimum Unit Voltage cell No. |
| 单体最高最低温度Ma ximum minimum temperature of monomer | 0x92 | 发送Send | Byte0~Byte7:Reserved |
| | | 返回Return | Byte0 : 最高单体温度值 (40 Offset, °C) maximum monomer temperature (40 Offset, °C) Byte1 : 最高单体温度cell号 Maximum monomer temperature cell No. Byte2 : 最低单体温度值 (40 Offset, °C) minimum monomer temperature (40 Offset, °C) Byte3 : 最低单体温度cell号 Minimum Monomer Temperature cell No. |
| 充放电、MOS状态Ch arge/discharge, MOS status | 0x93 | 发送Send | Byte0~Byte7:Reserved |
| | | 返回Return | Byte0 : 充放电状态 (0静止, 1充电, 2放电) charge/discharge status (0 stationary ,1 charged ,2 discharged) Byte1 : 充电MOS管状态 charging MOS tube status Byte2 : 放电MOS管状态 discharge MOS tube state Byte3:BMS life (0~255循环) BMS life(0~255 cycles) Byte4~Byte7:剩余容量 (mAHH) residual capacity (mAHH) |
| 状态信息1 Status Information 1 | 0x94 | 发送Send | Byte0~Byte7:Reserved |
| | | 返回Return | Byte0 : 电池串数 battery string Byte1 : 温度个数 temperature Byte2:充电器状态 (0断开, 1接入) charger status (0 disconnected ,1 connected) Byte3 : 负载状态 (0断开, 1接入) load status (0 disconnected ,1 access) Byte4 : Bit 0: DI1 state Bit 1: DI2 state Bit 2: DI3 state |



| | | | |
|--------------------------------------|------|----------|---|
| | | | Bit 3: DI4 state Bit 4: DO1 state Bit 5: DO2 state Bit 6: DO3 state Bit 7: DO4 state Byte 5~Byte6 :充放电循环次数charge/discharge cycles Byte7:Reserved |
| 单体电压1~48 Cell voltage 1~48 | 0x95 | 发送Send | Byte0~Byte7:Reserved |
| | | 返回Return | 每个单体电压占2byte, 根据实际单体个数发送, 最大96byte, 分16帧发送Each unit voltage of 2 byte, according to the actual number of units sent, a maximum of 96 byte, divided into 16 frames sent Byte0 : 帧序号, 从0开始, 0xFF为无效frame number, starting from 0, 0xFF invalid Byte1~byte6 : 单体电压 (1mV) monomer voltage (1 mV) Byte7:Reserved |
| 单体温度1~16 Monomer temperature 1~16 | 0x96 | 发送Send | Byte0~Byte7:Reserved |
| | | 返回Return | 每个温度占1byte, 根据实际使用温度个数发送, 最大21byte, 分3帧发送Each temperature is 1 byte, sent according to the actual number of temperature used, a maximum of 21 byte, divided into 3 frames Byte0 : 帧序号, 从0开始 frame number, starting at 0 Byte1~byte7 : 单体温度 (40 Offset, °C) monomer temperature (40 Offset, °C) |
| 单体均衡状态 Monomer equilibrium state | 0x97 | 发送Send | Byte0~Byte7:Reserved |
| | | 返回Return | 0 : 关闭OFF 1 : 开启ON Bit0 : 单体1均衡状态 monomer 1 equilibrium state ... Bit47 : 单体48均衡状态monomer 48 equilibrium state Bit48~Bit63 : reserved |
| 电池故障状态 Battery failure status | 0x98 | 发送Send | Byte0~Byte7:Reserved |
| | | 返回Return | 0 -> No error 1 -> Error Byte 0 Bit 0: 单体电压过高一级告警one stage warning of unit over voltage Bit 1: 单体电压过高二级告警one stage warning of unit over voltage Bit 2: 单体电压过低一级告警one stage warning of unit over voltage Bit 3: 单体电压过低二级告警two stage warning of unit over voltage Bit 4: 总压过高一级告警Total voltage is too high One alarm Bit 5: 总压过高二级告警Total voltage is too high Level two alarm |



| | | |
|--|--|---|
| | | <p>Bit 6: 总压过低一级告警 Total voltage is too low One alarm Bit 7: 总压过低二级告警 Total voltage is too low Level two alarm</p> <p>Byte 1</p> <p>Bit 0: 充电温度过高一级告警 Charging temperature too high. One alarm Bit 1: 充电温度过高二级告警 Charging temperature too high. Level two alarm Bit 2: 充电温度过低一级告警 Charging temperature too low. One alarm Bit 3: 充电温度过低二级告警 Charging temperature's too low. Level two alarm Bit 4: 放电温度过高一级告警 Discharge temperature is too high. One alarm Bit 5: 放电温度过高二级告警 Discharge temperature is too high. Level two alarm Bit 6: 放电温度过低一级告警 Discharge temperature is too low. One alarm Bit 7: 放电温度过低二级告警 Discharge temperature is too low. Level two alarm</p> <p>Byte 2</p> <p>Bit 0: 充电过流一级告警 Charge over current. Level one alarm Bit 1: 充电过流二级告警 Charge over current, level two alarm Bit 2: 放电过流一级告警 Discharge over current. Level one alarm Bit 3: 放电过流二级告警 Discharge over current, level two alarm Bit 4: SOC过高一级告警 SOC is too high an alarm Bit 5: SOC过高二级告警 SOC is too high. Alarm Two Bit 6: SOC过低一级告警 SOC is too low. level one alarm Bit 7: SOC过低二级告警 SOC is too low. level two alarm</p> <p>Byte 3</p> <p>Bit 0: 压差过大一级告警 Excessive differential pressure level one alarm Bit 1: 压差过大二级告警 Excessive differential pressure level two alarm Bit 2: 温差过大一级告警 Excessive temperature difference level one alarm Bit 3: 温差过大二级告警 Excessive temperature difference level two alarm</p> <p>Byte 4</p> <p>Bit 0: 充电MOS过温警告 charging MOS overtemperature warning Bit 1: 放电MOS过温警告 discharge MOS overtemperature warning Bit 2: 充电MOS温度检测传感器故障 charging MOS temperature detection sensor failure Bit 3: 放电MOS温度检测传感器故障 discharge MOS temperature detection sensor failure Bit 4: 充电MOS粘连故障 charging MOS adhesion failure Bit 5: 放电MOS粘连故障 discharge MOS adhesion failure</p> |
|--|--|---|



| | | |
|--|--|--|
| | | <p>Bit 6: 充电MOS断路故障 charging MOS breaker failure Bit 7: 放电MOS断路故障 discharge MOS breaker failure</p> <p>Byte 5</p> <p>Bit 0: AFE采集芯片故障 AFE acquisition chip malfunction Bit 1: 单体采集掉线 monomer collect drop off Bit 2: 单体温度传感器故障 Single Temperature Sensor Fault Bit 3: EEPROM存储故障 EEPROM storage failures Bit 4: RTC时钟故障 RTC clock malfunction Bit 5: 预充失败 Precharge Failure Bit 6: 整车通信故障 vehicle communications malfunction Bit 7: 内网通信模块故障 intranet communication module malfunction</p> <p>Byte 6 :</p> <p>Bit 0: 电流模块故障 Current Module Failure Bit 1: 内总压检测模块故障 main pressure detection module Bit 2: 短路保护故障 Short circuit protection failure Bit 3: 低压禁止充电故障 Low Voltage No Charging Bit 4~Bit7: Reserved</p> <p>Byte7 : 故障码 (如0x03, 则显示“故障码3”, 0不用显示) fault code (if 0 x 03, show "fault code 3", 0 do not show)</p> |
|--|--|--|